

Operating instructions in brief:

Answering machine / remote interrogation

Function	Keyboard	Function keys of the drive
Setting day / time		Keep key delete depressed and tap the playback or the On/Off key; after reaching the day, release the delete key and keep it depressed again and tap the playback or On/Off key until the current hour is announced. Afterwards repeat the process for the minute setting.
New announcement text		Press the stop key until the symbol flashes and afterwards record the text.
Delete announcement text		Press the stop key, during the announcement press the delete key
Working mode and number of call signals		Keep the On/Off key depressed
Message playback	②	Playback ▶
Jump to previous message	④	On/Off ◀
Jump to next message	⑥	2x playback ▶
Repeat current message	⑥	playback ▶
Stop current message	⑦	
Delete selected messages	⑤	delete
Deleting all messages	⑤	delete
Recovering deleted messages	①	stop
Answering machine On/Off	⑧	On/Off ◀